



# Compact, Wireless 3-in-1 Mono Laser Printer

Simple set up, simple to use

## DCP-L1632W



PRINT



SCAN



COPY



WIRELESS



WIRELESS



AIRPRINT

[www.brother.co.za](http://www.brother.co.za)

## Compact, Wireless, Monochrome 3-in-1 Laser Printer

The ideal device for your home and small office.

The compact DCP-L1632W is designed to fit seamlessly into your space with flexible connectivity options making it simple to set up and simple to use.



PRINT



SCAN



COPY



5GHz



AIRPRINT

### DCP-L1632W



### Key features:

- Print up to 20 pages per minute
- Copy speed up to 20 cpm
- Scan to email, file, image, OCR
- 128MB Memory Capacity
- Wi-Fi Direct / Wireless Connectivity / Wired
- Mobile Connect
- 150 sheet paper tray
- 1,500 page inbox toner
- Free 3-year Carry-in Warranty
- 2 Line LCD control panel
- Fast ethernet, 2.4GHz and 5GHz WiFi and USB

### Super compact

Save valuable desk space with this stylish printer. The compact footprint makes this device an ideal fit for your home workspace.

### Simple to use

Enjoy a hassle-free experience. Set up and use your device with ease with Brother Mobile Connect and a range of flexible connectivity options including 5GHz WiFi, fast ethernet and USB.

### Connect for more control

Set up and print on the go with Brother Mobile Connect. Control all your Brother printers from your fingertips. Easily check supplies, access your scanned documents history and personalise your frequently used features.



### Secure by design



To keep pace with the ever-evolving legislation on privacy and data security, our devices offer the latest industry-standard security features to securely protect your data. Our security experts continuously research new enhancements to products, solutions and services to proactively ensure all our products are 'secure by design'.

The DCP-L1632W uses triple-layer security at a device, network and document level, offering added peace of mind, guaranteeing that the integrity of your data is maintained at every step.

## General

### Technology

Electrophotographic Laser

### Memory

128MB

### Control panel

2 Line LCD with keys  
(No back light)

### Local Interface

Hi-Speed USB 2.0

### Wired Network

Fast Ethernet

### Wireless Network

2.4GHz and 5GHz Support

### Carton Contents

Device, Inbox Toner, Drum,  
Power Supply Cord, Quick  
Set-Up Guide

## Print

### Print Speed (A4)

1-Sided: 20 pages pm Mono

### FPOT

(First Print Out Time)

Up to 10.0 Seconds Mono

### Resolution

Up to 2400 x 600dpi

## Printer Functions

### N-up Printing

Reduce up to 25 pages into  
a single page

### Poster Printing

Enlarge a single page into a  
poster using 2x2, 3x3, 4x4  
or 5x5 pages

### Toner Save Mode

Use the Toner Save Mode to  
reduce toner consumption  
without affecting print speed

### Watermark Printing

Watermark your documents  
with predefined text, custom  
logo or custom messages

### ID Printing

Add identification to your printed  
documents (date and time,  
short custom message or PC  
username)

### Booklet Printing

Print documents in A5 booklet  
format using manual 2-sided  
print

### Print Profiles

Store your favourite driver  
settings as profiles to easily  
recall them

### Manual 2-Sided Print

Yes

### Reverse Print

Rotate the content of a printed  
document by 180°

### Print Complete Notice

A printing notification can be  
set to go to your computer  
(Network only)

## Printer Drivers

### Windows

Windows 11  
(32 and 64 bit editions)  
and more

### macOS

Printing via macOS requires the  
use of AirPrint. Mac drivers are  
not provided.

Visit [support.brother.com](https://support.brother.com) for the full list of supported OS and  
to download the latest drivers and software.

### Linux

CUPS, LPD/LPRng  
(x86/x64 environment)

### ChromeOS

Supports native  
ChromeOS printing

## Paper Handling<sup>11</sup>

**Paper Input  
Standard Tray**  
150 Sheets

**Paper Output**  
50 Sheets A4

**Media Sizes  
Standard Tray**  
A4, Letter, Legal, Folio, A5, A5  
(Long Edge), B5 (JIS), B5 (ISO),  
Executive, 16K (195 x 270mm)

**Scanner Glass**  
Up to A4 / Letter

**Media Type and Weights  
Standard Tray**  
Plain Paper, Recycled Paper  
65 - 105gsm

## Mobile and Web Connectivity

**Brother Mobile Connect <sup>17</sup>  
(Android)**  
Print from, scan to, preview  
copies and check the machine  
status from an Android device

**Brother Mobile Connect <sup>17</sup>  
(iPad / iPhone)**  
Print from, scan to, preview  
copies and check the machine  
status from an iPad / iPhone

**Apple AirPrint <sup>17</sup>**  
Print from and scan to most  
common file types from any  
AirPrint enabled application

**Brother Print Service  
Plugin<sup>17</sup>**  
Print from an Android devices  
without a dedicated App

**Mopria™ <sup>17</sup>**  
Print most common file types  
from Mopria™ supported  
Android devices

## Copy

**Copy Speed (A4)**  
1-Sided: 20 pages pm Mono

**Resolution**  
Up to 600 x 600dpi

**FCOT  
(First Copy Out Time)**  
Up to 16 seconds Mono

**Grey Scale**  
256 Shades of grey  
(8 bit for each colour)

## Copy Functions

**Multi-Copying/Stack/Sort**  
Makes multiple copies of a  
document. Stacks up to to 99  
copies of each page or sorts into  
original document order

**Enlargement/Reduction  
Ratio**  
Reduce or increase document  
sizes from 25% to 400% in 1%  
increments

**N in 1 Copying**  
Allows the user to compress 2 or  
4 pages on to a single A4 sheet

## Scan

**Scanner Type**  
CIS (Contact Image Sensor)

**Colour and Mono  
Scanning**  
Yes

**Scan Resolution from  
Scanner Glass**  
600 x 1200dpi

**Interpolated Scan  
Resolution**  
Brother Scanner Utility  
enhances up to 19,200  
x 19,200dpi

**Colour Depth**  
30 bit colour processing (Input)  
24 bit colour processing (Output)

**Grey Scale**  
10 bit colour processing (Input)  
8 bit colour processing (Output)

## Scanner Functions

**Standard Functions** <sup>17</sup>  
Scan to E-mail, Image, File

## Scanner Drivers

**Windows**  
TWAIN and WIA  
Windows 11  
(32 and 64 bit editions)

**MacOS**  
Scanning via MacOS requires the use of AirPrint. Mac drivers are not provided

**Linux**  
SANE (x86/x64 environment)

**ChromeOS**  
Supports native ChromeOS scanning

Visit [support.brother.com](https://support.brother.com) for the full list of supported OS and to download the latest drivers and software.

## Fleet Management Tools

**BRAdmin** <sup>16,17</sup>  
LAN/WAN management software

**Status Monitor** <sup>16</sup>  
Monitor the status of your machine from your computer

## Software

**Brother iPrint&Scan Desktop** <sup>15,17</sup>  
Print from and check the machine status from Windows or macOS PC

**PaperPort SE 14** <sup>16,17</sup>  
Document management and sharing program from Tungsten Automation

**Utilities**  
Provides setup guides, manual, FAQ, troubleshooting and contact to Brother customer service

**Easy Setup**  
Simple access to drivers and software for the installation of your Brother machine from [support.brother.com](https://support.brother.com)

## Connectivity

**Wired Network**  
Fast Ethernet  
(10Base-T/100Base-TX)

**Wireless Network**  
IEEE 802.11a/b/g/n  
(Infrastructure Mode)  
IEEE 802.11a/g/n  
(Wi-Fi Direct)

**Wi-Fi Direct** <sup>®</sup>  
Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported)

**Wireless Setup Support**  
Wi-Fi Protected Setup (WPS)

**Wireless Applications**  
Vertical Pairing

**Mobile**  
Print or scan from your mobile device with Brother Mobile Connect, Airprint, Mopria

**Local Interface**  
Hi-Speed USB 2.0

## Security Features

### Wired Network Security

SMTP-AUTH, SSL/TLS  
(SMTP, HTTP, IPP), SNMP v3

### Wireless Network Security

WEP 64/128 bit, WPA-PSK  
(TKIP/AES), WPA2-PSK  
(TKIP/AES), WPA3-SAE (AES),  
\*WIFI Direct supports  
WPA2-PSK (AES) only

SMTP-AUTH, SSL/TLS  
(SMTP, HTTP, IPP), SNMP v3

### IPv4

ARP, RARP, BOOTP, DHCP,  
APIPA (Auto IP), WINS/NetBIOS  
name resolution, DNS Resolver,  
mDNS, LLMNR responder,  
LPR/LPD, Custom Raw  
Port/Port9100, SMTP Client,  
IPP/IPPS, FTP Server,  
SNMPv1/v2c/v3, HTTP/HTTPS  
server, TFTP client and server,  
ICMP, Web Services  
(Print/Scan), SNTP Client

### IPv6

NDP, RA, DNS resolver, mDNS,  
LLMNR responder, LPR/LPD,  
Custom Raw Port/Port9100,  
IPP/IPPS, SMTP Client, FTP  
Server, SNMPv1/v2c/v3,  
HTTP/HTTPS server, TFTP  
client and server, ICMPv6,  
Web Services (Print/Scan),  
SNTP Client

### IP Filter

Restrict which network users  
can or cannot access the device  
over the network (IPv4 only)

### E-mail Notifications

Automatically have the device  
send e-mail alerts when it  
requires attention, such as  
when the toner is low or needs  
replacing

### E-mail Reports

Receive usage reports on a  
regular basis via e-mail

### Automatic Intrusion Detection

All Brother Print devices are  
secure by design. Devices  
automatically recognise security  
attacks and take preventative  
measures, including rebooting  
where necessary, to ensure the  
device remains secure

### Firmware Updates

In addition to allowing automatic  
update alerts to install the latest  
version the printer can be set  
to not receive older firmware  
versions to avoid downgrade by  
an unauthorised user

### Firmware Encryption

During update firmware is  
transferred over a trusted HTTPS  
encrypted connection

### Digitally-signed Firmware

The firmware for Brother print  
and scan devices is digitally  
signed and secure

### Certificate Management

Use the default standard  
self-signed, create a custom  
self-signed certificate, certificate  
signing request (CSR), or  
external public certificate &  
private key for protected network  
communication

### Syslog

Allows IT Admin to access a  
single application (SIEM tool) to  
get device status updates for  
audit purposes over Syslog

### Port-based Network Access Control

(IEEE 802.1x)  
Brother devices are in full  
compliance with this standard,  
to allow connection to an 802.1x  
EAP (Extensible Authentication  
Protocol) protected network

### Restrict network protocols

The Protocol Control feature  
allows an administrator to restrict  
communication protocols (e.g.  
FTP, Telnet) as required

## Supplies and Consumables

### Inbox Toner <sup>7</sup>

1 x 1,500 pages (BK)

### Standard Yield Toner <sup>7</sup>

TN-114 - 1,500 pages

### Drum Unit

DR-114 Approx. 10,000 pages  
at 1 page per job

## Dimensions and Weights

### With Carton (WxDxH)

481 x 436 x 406mm - 9.20kg

### Without Carton (WxDxH)

385 x 340 x 255mm - 7.30kg

Duty Cycle

Recommended Monthly  
Up to 2,000 pages

Operating Environment

Power Requirement  
220 - 240V  
AC 50/60Hz

Operating Environment  
Humidity 20 - 80%  
10°C - 32.5°C  
50°F - 90.5°F

Storage Environment  
Humidity 20 - 80%  
0°C - 40°C  
32°F - 104°F

Environment

Approx Power Consumption<sup>13,23</sup>  
Printing: 380W  
Copying: 380W  
Ready: 40W  
Sleep: 2.7W  
Deep Sleep: 1.0W  
Power Off: 0.28W

TEC Value  
0.29 kWh/week

Sound Pressure<sup>12</sup>  
PC Printing (Mono):  
52.0dB(A)  
Ready: 18.0dB(A)

Sound Power<sup>12</sup>  
Printing: 6.66B(A)  
Ready: 4.69B(A)  
Deep Sleep: 4.68B(A)

Warranty

Brother 3-Year Warranty

When you purchase a Brother printer and our genuine inks or toners, we'll support you every step of the way with our FREE 3-year\* warranty commitment. YOU DO NOT NEED TO REGISTER YOUR PRODUCT, our warranty is automatic when you purchase your Brother printer. To keep your Brother machine running in optimal condition, we recommend using only Brother Genuine Consumables, this will ensure you automatically enjoy our exclusive 3-year\* warranty.



\*Effective 1 September 2025. Valid only for products purchased in South Africa.

- 7    Approx. declared yield value in accordance with ISO/IEC 19752
- 11   Capacity calculated with 80gsm paper
- 12   Sound pressure and sound power level in accordance with ISO 7779
- 13   Power consumption power off is measured according to IEC 62301 Edition 2.0
- 15   Windows and macOS only
- 16   Windows only
- 17   Optional download
- 23   Power consumption is measures using ENERGY star ver 3.1 test method network configuration



App Store, Mac, macOS and AirPrint are trademarks of Apple Inc., registered in the U.S. and other countries. Google Play and the Google Play logo are trademarks of Google LLC.



Brother International South Africa

96 Sovereign Drive, Route 21 Corporate Park, Irene

Tel 0861 brother    Email info@brother.co.za

www.brother.co.za    https://support.brother.com/



Working with you for a sustainable future.



All specifications correct at time of publication and are subject to change without notice. Brother and its logo are trademarks of Brother Industries LTD., Japan. All registered trademarks referenced herein are the property of their respective companies.