



Your Efficient 3-in-1 Mono Laser Printer

Easy to set up and connect for
fast flawless printing

DCP-L2640DW



PRINT



SCAN



COPY

www.brother.co.za

Your Efficient 3-in-1 Mono Laser Printer

Work from anywhere, at home or in the office with the easily connected Brother DCP-L2640DW. Hosting a range of efficiency-boosting features, this 3-in-1 mono laser printer saves you time with fast flawless printing and quick scan speeds, automatic 2-sided print, a generous paper tray capacity and large automatic document feeder.

Set up with ease and download the Brother Mobile Connect App, enabling you to print and scan from virtually anywhere.

DCP-L2640DW



Key features:

- Print up to 34 pages per minute
- Auto duplex print, up to 16 sides per minute
- 2 Line LCD control panel
- Fast ethernet, USB and Wi-Fi Direct
- 256MB Memory
- 50 Sheet Automatic Document Feeder (ADF)¹¹
- 250 Sheet paper input tray¹¹
- 1,200 Page yield inbox toner
- 3,000 maximum yield available⁷

Work smarter

The DCP-L2640DW is designed to increase efficiency, with fast print speeds helping you to work smarter. The Automatic Document Feeder and 2-sided print features save you time, enabling you to get on with other tasks. Scan your documents in colour or mono and send directly to your desktop or mobile device.

Effortless

Make your day easier and your printing effortless, with simple set up and fast, wireless ethernet or USB connection. This efficient DCP-L2640DW is a breeze to operate using the easy to navigate control panel.

The perfect partner

High quality print technology ensures that your output is flawless and professional every time. The expertly designed DCP-L2640DW has a high capacity paper input and output tray allowing you to print for longer, while the compact and quiet form enables you to work without interruption in smaller workspaces.

Print longer

The DCP-L2640DW keeps your printing costs down using a separate drum and toner unit, and the generous 1,200 pages⁷ inbox toner supporting your higher print volume needs. Toner is easy to change and a high yield toner is available, printing up to 3,000 pages⁷, reducing your cost per page and replacement frequency.

Secure by design

To keep pace with the ever-evolving legislation on privacy and data security, our devices offer the latest industry-standard security features to securely protect your data. Our security experts continuously research new enhancements to products, solutions and services to proactively ensure all our products are 'secure by design'.

The DCP-L2640DW provides a range of robust features. It uses triple-layer security at a device, network and document level. This offers added peace of mind and guarantees that the integrity of your data is maintained at every step.

Print from anywhere

With Brother Mobile Connect, you can fully operate your Brother printer from anywhere. Print and scan documents on the move. You can also personalise your frequently used features and unlock a revolutionary way of printing from your mobile device. Download the app on your mobile device to get started.



General

Technology

Electrophotographic Laser

Memory

256MB

Control panel

2 Line LCD with keys,
White Back Light

Local Interface

Hi-Speed USB 2.0

Wired Network

Fast Ethernet

Wireless Network

2.4GHz Support
Wi-Fi Direct

Carton Contents

Printer, Inbox Toner, Drum,
Power Supply Cord, USB Cable,
Quick Set-Up Guide

Print

Print Speed

1-Sided: 34ppm Mono
2-Sided: 16 sides
per minute Mono

FPOT (First Print Out Time)

Up to 8.5 Seconds Mono

Quiet Mode

A mode to reduce the printing
noise

Resolution

Up to 1200 x 1200dpi

Print Languages

PCL6, BR-Script3,
PDF Version 1.7

Embedded Fonts (PCL)

73 scalable fonts,
12 bitmap fonts

Embedded Barcodes (PCL)

16 bar codes*

*Code39, Interleaved 2 of 5,
FIM (US-PostNet), Post Net
(US-PostNet), EAN-8, EAN-13,
UPC-A, UPC-E, Codabar, ISBN
(EAN), ISBN (UPC-E), Code128
(set A, set B, set C), EAN128
(set A, set B, set C), Code93,
GS1Databar, MSI

Embedded Fonts (Postscript)

66 scalable fonts

Printer Functions

N-up Printing

Reduce pages into
a single page layout

Poster Printing

Enlarge a single page into a
poster using 2x2, 3x3, 4x4
or 5x5 pages

Toner Save Mode

Use the Toner Save Mode to
reduce toner consumption
without affecting print speed

Watermark Printing

Watermark your documents
with predefined text, custom
logo or custom messages

ID Printing

Add identification to your printed
documents (date and time,
short custom message or
PC username)

Booklet Printing

Print documents in A5 booklet
format using automatic or
manual 2-sided print

Print Profiles

Store your favourite driver
settings as profiles to easily
recall them

Manual 2-Sided Print

Manual 2-sided printing
(recommended for media
not supported by automatic
2-sided print)

Print Complete Notice

A printing notification can be
set to go to your computer
(Network only)

Printer Driver

Windows

Windows 11
(32 and 64 bit editions)
and more

macOS

Printing via macOS requires the use of AirPrint. Mac drivers are not provided.

Linux

CUPS, LPD/LPRng
(x86/x64 environment)

ChromeOS (Print/Scan Only)

Supports native
ChromeOS printing

PCL Driver

Universal Printer Driver
(Windows)
(PCL5e/BRScript)

PostScript Universal Printer Driver

Driver for Windows that enables you to print to any network or locally connected Brother printer

Visit support.brother.com for the full list of supported OS and to download the latest drivers and software.

Paper Handling¹¹

Paper Input Standard Tray

250 Sheets

Manual Feed Slot

1 Sheet

Automatic Document Feeder (ADF)

50 Sheets

Paper Output

120 Sheets A4

Envelope Printing

From manual feed slot

Media Sizes Standard Tray

A4, Letter, B5(JIS), B5(ISO),
A5, A5(Long Edge), B6(JIS),
A6, Executive, A4 Short,
16K(195x270mm)

Manual Feed Slot

Width 76.2 to 215.9 mm,
Length 127 to 355.6 mm
Envelope; COM-10, DL, C5,
Monarch

ADF

Width: 105 to 216 mm
Length: 147 to 356 mm

Scanner Glass

Up to A4/LTR

Auto 2-Sided

A4

Media Type and Weights Standard Tray

Plain Paper, Thin Paper,
Recycled Paper,
Thick Paper
60-163gsm

Manual Feed Slot

Plain Paper, Thin Paper, Thick
Paper, Thicker Paper, Recycled
Paper, Bond, Label, Envelope,
Env. Thin, Env. Thick
60-230gsm

ADF

Plain Paper, Recycled Paper
60 to 105gsm

Auto 2-Sided

Plain Paper, Thin Paper,
Recycled Paper
64-105gsm

Mobile and Web Connectivity

Brother Mobile Connect¹⁷ (Android)

Print from, scan to, preview
copies and check the machine
status from an Android device

Brother Mobile Connect¹⁷ (iPad / iPhone)

Print from and check the
machine status from an
iPad / iPhone

Apple AirPrint¹⁷

Print from and scan to most
common file types from any
AirPrint enabled application

Brother Print Service Plugin¹⁷

Print from any Android devices
without a dedicated App

Mopria™¹⁷

Print most common file types
from Mopria™ supported
Android devices

Copy

Copy Speed

34ppm Mono
(Manual Duplex)

Resolution

Up to 600 x 600dpi

FCOT

(First Copy Out Time)
Up to 10 Seconds Mono

Grey Scale

256 shades of grey

Copy Functions

Multi-Copying/Stack/Sort

Makes up to 99 copies of each page / Stacks or Sorts

Enlargement/Reduction Ratio

Reduce or Increase document sizes from 25% to 400% in 1% increments

N in 1 Copying

Allows the user to compress 2 or 4 pages on to a single A4 sheet

Scan

Scanner Type

CIS (Contact Image Sensor)

Colour and Mono Scanning

Yes

Scan Speed³

22.5ipm Mono and
7.5ipm Colour

Scan Resolution from ADF

600 x 600dpi

Scan Resolution from Scanner Glass

1200 x 1200dpi

Interpolated Scan Resolution

Brother Scanner Utility enhances up to 19,200 x 19,200 dpi

Colour Depth

30 bit colour Processing (Input)
24 bit colour Processing (Output)

Grey Scale

10 bit colour Processing (Input)
8 bit colour Processing (Output)

Scanner Functions

Supported File Formats

Including PDF (PDF/A, Secure PDF, Signed PDF, Searchable⁷)
JPEG, TIFF

Standard Functions¹⁷

Scan to E-mail, OCR ,
Image, File

Network Scanning¹⁶

Scan to FTP, FTPS, Sharepoint
(iPrint&Scan for Windows only)

Scan Features

Auto Deskew from ADF only
(iPrint&Scan for Desktop)

Scan To Microsoft Office

Scan to Word (.docx),
PowerPoint (.pptx), Excel (.xlsx)
for Microsoft Office

Scan Profile¹⁵

Create up to 25 profiles for an easy way to store multiple scan settings (scan to FTP/Sharepoint)

Scanner Drivers

Windows

TWAIN and WIA
Windows 11
(32 and 64 bit editions)

Visit support.brother.com for the full list of supported OS and to download the latest drivers and software.

macOS

Scanning via macOS requires the use of AirPrint. Mac drivers are not provided.

Linux

SANE (32 and 64 bit editions)

ChromeOS

Supports native ChromeOS scanning

Fleet Management Tools

BRAdmin Pro^{16,17}
LAN/WAN management software

Embedded Web Server
Web based print management software embedded onto the device

Status Monitor¹⁶
Monitor the status of your machine from your computer

Driver Deployment Wizard^{16,17}
Easily create print drivers for hassle free deployment over your network

Software

Brother iPrint&Scan Desktop^{15,17}
Print from, scan to, preview copies and check the machine status from Windows or macOS PC

PaperPort SE 14^{16,17}
Document management and sharing program from KOFAX

Utilities
Provides setup guides, manual, FAQ, troubleshooting and contact to Brother customer service

Easy Setup
Simple access to drivers and software for the installation of your Brother machine from support.brother.com Windows/Mac

Connectivity

Wired Network
Fast Ethernet
(10Base-T/100Base-TX)

Wi-Fi Direct[®]
Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported)

Wireless Setup Support
Wi-Fi Protected Setup (WPS))

Wireless Applications
Vertical Pairing

Mobile
Print or scan from your mobile device with Brother Mobile Connect, Airprint, Mopria

Local Interface
Hi-Speed USB 2.0

Warranty

Brother 3-Year Warranty

When you purchase a Brother printer and our genuine inks or toners, we'll support you every step of the way with our FREE 3-year* warranty commitment. YOU DO NOT NEED TO REGISTER YOUR PRODUCT, our warranty is automatic when you purchase your Brother printer. To keep your Brother machine running in optimal condition, we recommend using only Brother Genuine Consumables, this will ensure you automatically enjoy our exclusive 3-year* warranty.

*Effective 1 September 2025. Valid only for products purchased in South Africa.



Security Features

Wired Network Security

APOP*, SMTP-AUTH, SSL/TLS (SMTP, POP3, IMAP4,FTP)*, SNMP v3, 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), OAuth(SMTP, POP3, IMAP4) *When Internet FAX is downloaded.

IPv4

ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, SMTP Client, IPP/PPS, FTP Client and Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, Web Services (Print/Scan), SNTP Client

IPv6

NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/PPS, SMTP Client, FTP Client and Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMPv6, Web Services (Print/Scan), SNTP Client

IP Filter

Restrict which network users can or cannot access the device over the network (IPv4 only)

E-mail Notifications

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

E-mail Reports

Receive usage reports on a regular basis via e-mail

Automatic Intrusion Detection

All Brother Print devices are secure by design. Devices automatically recognise security attacks and take preventative measures, including rebooting where necessary, to ensure the device remains secure

Firmware Updates

In addition to allowing automatic update alerts to install the latest version the printer can be set to not receive older firmware versions to avoid downgrade by an unauthorised user

Port-based Network Access Control

(IEEE 802.1x)
Brother devices are in full compliance with this standard, to allow connection to an 802.1x EAP (Extensible Authentication Protocol) protected network

Restrict network protocols

The Protocol Control feature allows an administrator to restrict communication protocols (e.g. FTP, Telnet) as required

Supplies and Consumables

Inbox Toner⁷

1 x 1,200 pages

Standard Yield Toner⁷

TN2500 - 1,200 pages

High Yield Toner⁷

TN2500XL - 3,000 pages

Drum Unit

DR2500 Approx 15,000 pages at 1 page per job

Dimensions and Weights

With Carton (WxDxH)

580 x 517 x 434mm - 14.40kg

Without Carton (WxDxH)

410 x 399 x 319mm - 10.30kg

| | | | |
|-----------------------|------------------------|--|--|
| Operating Environment | Power Requirement | Operating Environment | Storage Environment |
| | 220-240V AC 50/60Hz | Humidity 20 - 80 % 10°C - 32.5°C 50°F - 90.5°F | Humidity 35 - 85 % 0°C - 40°C 32°F - 104°F |

| | | | |
|-------------|---|---|---|
| Environment | Approx Power Consumption ^{13,23} | TEC Value | Sound Pressure ¹² |
| | Copying: 490W Copying in quiet mode: 280W Printing: 470W Printing in quiet mode: 270W Ready: 43W Sleep: 4.1W Deep Sleep: 0.6W Power Off: 0.08W | 0.39 kWh/week | PC Printing (Mono): Approx. 49.0dB(A) Ready: 30.0db(A) Quiet Mode: 44.0db(A) |
| | | Sound Power ¹² | Toner Save |
| | | Printing: 6.63B(A) Ready: Inaudible Quiet Mode: 6.12B(A) Deep Sleep: Inaudible | This reduces the toner consumption to get more pages from your consumables |

3

Scan Speeds based on ISO/IEC 17991

7

Approx. declared yield value in accordance with ISO/IEC 19752

11

Capacity calculated with 80gsm paper

12

Sound pressure and sound power level in accordance with ISO 7779

13

Power consumption power off is measured according to IEC 62301 Edition 2.0

15

Windows and macOS only

16

Windows only

17

Optional download

18

Requires an Internet connection

23

Power consumption is measured using ENERGY STAR Ver 3.1 test method network configuration



All specifications correct at time of publication and are subject to change without notice. Brother and its logo are trademarks of Brother Industries LTD., Japan. All registered trademarks referenced herein are the property of their respective companies.

Brother International South Africa
96 Sovereign Drive, Route 21 Corporate Park, Irene
Tel 0861 brother Email info@brother.co.za
www.brother.co.za https://support.brother.com/



Working with you for a sustainable future.