



Professional colour laser printer

with cost-effective, high-quality colour printing

HL-L9430CDN



PRINT



ADVANCED
SOLUTIONS

www.brother.co.za



Professional colour laser printer

High-quality, cost-effective professional colour printing with premium results. Built for business, this device is designed to deliver a professional performance - with high-speed, glossy colour printing you can rely on with the flexibility to be tailored to suit you and your business

HL-L9430CDN



Key features:

- Print up to 40 pages per minute
- 2-sided print, up to 28 sides per minute
- 8.76cm colour touchscreen LCD
- NFC (Near-Field Communication) for secure authentication and mobile print
- 1GB internal memory
- 520 sheet paper input tray expandable to 2600
- 9,000 page (BK), 6,500 page (C/M/Y) inbox toners¹

Simple. Effortless. Intelligent

The HL-L9430CDN comes with Cloud Secure Print as standard, so you can print securely without installing additional drivers or apps. You also have the option to further enhance your device with third party solutions, meaning that you can have a fully integrated print, capture and output management solution all from one provider.

Flexibility that saves money

A wide range of professional finishing options are available for the HL-L9430CDN for optimal efficiency. If you need a mailbox to sort your printed documents, your printer can easily be transformed to help improve business productivity. Boost paper capacity with additional paper trays or Tower tray unit, transforming your HL-L9430CDN to a floor-standing printer.

Secure by design

As working conditions change, security is more critical than ever. The HL-L9430CDN comes with enterprise level security, supporting the latest industry-standard security protocols to keep your data secure. You can further protect your device by setting up user authentication, whereby access to certain settings and functions are restricted to authorised users or groups.



When quality and performance work together

Our most advanced colour printing technology is guaranteed to make the right impression when it counts, with vibrant, professional colour prints. The robust design and long-life components provide confidence that your device will keep on performing without interruption.

Solutions ready

Streamlined business processes

With the ever changing workplace, it's important to continuously review and refine the way your business operates. Utilising the right technology can redefine business processes and bring surprising benefits.

Cloud Secure Print is a convenient built-in feature which enables you to easily send documents to print when you're away from home or the office. Remotely submit the print request via email to a Brother device with an active internet connection and securely retrieve print jobs when you are ready. Documents will only be printed when the sender enters a unique password on the destination device's control panel.



Unlock new possibilities with a range of business solutions

Whether you already use print management software or would like to understand how it can improve efficiency and security within your business, we are here to help.

You have the option to upgrade your device with intelligent Brother and third-party solutions, including integration with industry leading providers Kofax, and YSoft. This gives you complete flexibility in how you manage, secure and control your documents.

We work closely with our software partners across print management and document capture to create tailored solutions for your specific requirements. When we partner with a software vendor, we ensure your HL-L9430CDN works even harder to meet your needs.



General

Technology

Electrophotographic Laser

Laser Classification

Class 1 Laser Product

Memory

1GB Internal

Control Panel

8.76cm Colour
Touchscreen LCD

Local Interface¹⁷

Hi-Speed USB 2.0, USB 2.0
Host (Front | Rear)

Wired Network Interface

GigE (10Base-T/100Base-
TX/1000Base-T)

Mobile Print

Print from a mobile device to
your Brother printer

Wireless Network (optional)

2.4GHz Supp^o rt

Wi-Fi Direct™

Print wirelessly¹⁶ without having
to use a wireless access point
(both automatic and manual
methods supported)

Print

Print Speed⁸ (A4)

Up to 40ppm (pages per minute)

Print Speed⁸ 2-Sided (A4)

Up to 28 sides per minute
(14 sheets per minute)

Resolution

2,400dpi (2,400 x 600dpi),
600 x 600dpi

FPOT⁹

(First Print out Time)

Less than 10 seconds from
ready mode and standard tray

Warm Up Time

Less than 20 seconds from
sleep mode

Print Languages

PCL5e, PCL5c, PCL6,
(PCL XL Class3.0), BR-Script3,
PDF Version 1.7, XPS Version 1.0

Embedded Fonts (PCL)

73 scalable fonts,
12 bitmap fonts

Embedded Fonts (Postscript)

66 scalable fonts

Embedded Barcodes (PCL)

16 bar codes fonts - Code39,
Interleaved 2 of 5, FIM
(US-PostNet), Post Net
(US-PostNet), EAN-8, EAN-
13, UPC-A, UPC-E, Codabar,
ISBN(EAN), ISBN(UPC-E),
Code128 (set A,B, C),
EAN128 (set A,B,C), Code93,
GS1Databar, MSI

Printer Functions

N-up Printing³

Reduce up to 2, 4, 9 or 16 or
25 A4 pages into just one A4
page Mac (Airprint) up to 2, 4, 6,
9, or 16

Booklet Printing

Print documents in A5 booklet
format using automatic or
manual 2-sided print

Poster Printing⁴

Enlarge 1 A4 page into a poster
using 4, 9, 16 or 25 A4 pages

Watermark Printing⁴

Watermark your documents with
predefined or user-defined text

Direct Print

Print directly from a USB flash
memory drive. Supported
formats include; PDF 1.7, JPEG,
Exif+JPEG, PRN (created using
printer driver of model), TIFF
(scanned using brother model),
XPS version 1.0

Manual 2-Sided Print⁴

Manual 2-sided printing
(recommended for media not
supported by automatic
2-sided print)

ID Printing⁴

Add identification to your printed
documents (date & time, short
custom message or PC
username)

Carbon Copy⁴

Prints additional copies of the
same document to paper taken
from additional paper trays

Print Complete Notice

A printing notification can be set
to go to your computer when
printing

Match Media^{4/19}

Assign an ID to a specific tray to
make the selection of different
media types from a specific tray
easier

Skip Tray¹⁹

Configures your paper tray
selection to avoid specific trays/
media for regular printing

Printer Functions

Print Text in black⁴

Converts all text in your documents to black when printed

Storage Print

Easily retrieve and print your documents all of which are AES 256 encrypted and held within an attached USB Flash memory storage drive up to 8GB (not included)

Reverse Print⁴

Rotate the content of a printed document by 180°

Job Separation¹⁹

Insert a different coloured piece of paper between different print jobs to separate them for easy identification.

Secure Print⁴

Protect print jobs with a 4 digit release code required at the device in order for them to be printed

Printer Driver⁵

Windows¹⁸

Windows 10/11
(Home|Pro|Education|Enterprise)
(32 or 64 bit editions)
Windows 8.1
(32 or 64 bit editions)
Windows 7 SP1
(32 or 64 bit editions)
Windows Server
2022, 2019, 2016, 2012R2,
2012, 2008R2
Windows Server 2008 SP2
(32 & 64 bit editions)

Macintosh²¹

macOS 10.14.x or greater

Linux

CUPS, LPD/LPRng
(x86/x64 environment)

PCL Driver

Generic PCL XL driver

PostScript Universal Printer Driver

Driver for Windows that enables you to print to any network or locally connected Brother laser printer that supports PostScript

ChromeOS²³

Supports native ChromeOS printing

Paper Handling

Paper Input²

Standard (Tray 1)

520 Sheets

Multi Purpose Tray

100 Sheets, 15 Envelopes

Paper Output²

250 sheets face down
1 sheet face up (straight path)

Media Sizes

Standard (Tray 1)

Letter, Legal, Executive, A4, A5, A5 (Long Edge), A6, B5(ISO), Folio, 16K (195 x 270mm)

Multi Purpose Tray

Width: 76.2mm - 215.9mm
Length: 127mm - 355.6mm
Envelopes; C5, Com-10, DL, Monarch

Optional (Trays 2-5)

Letter, Legal, Executive, A4, A5, Mexico Legal, India Legal, Folio, 16K (195 x 270mm)

2-Sided Print

A4, Letter, Legal, Mexico Legal, India Legal, Folio
(Desired paper size can be selected manually)

Media Types

Standard (Tray 1)

Thin Paper, Plain Paper, Thick Paper, Thicker Paper, Recycled Paper

Multi Purpose Tray

Thin Paper, Plain Paper, Thick Paper, Thicker Paper, Recycled Paper, Bond Paper, Label, Envelope, Env. Thin, Env. Thick, Glossy Paper²⁰

Optional (Trays 2-5)

Thin Paper, Plain Paper, Thick Paper, Recycled Paper

2-Sided Print

Thin Paper, Plain Paper, Thick Paper, Thicker Paper, Recycled Paper, Glossy paper

Media Weights

Standard (Tray 1), Multi Purpose Tray

60 - 230gsm

Optional (Trays 2-5)

64 - 105gsm

Optional Mailbox Sorter

60 - 200gsm (with offset)

Paper Input / Output Sensors

Onscreen and optional email alert notifications when input trays are empty or running low or the output stack is full.

Mobile and Web Connectivity

Apple AirPrint

Print most common file types from any AirPrint enabled application

Brother Print Service Plugin⁵

Print from Android devices without a dedicated App

Brother Mobile Connect

Print from a mobile device running iOS or Android operating system

Mopria

Print most common file types from Mopria supported Android devices

Web Connect^{10, 15}

Without using a PC, download and print from Box, SharePoint Online, Dropbox, Evernote, OneDrive, Google Drive™, OneNote

Brother Apps¹⁰

Cloud Secure Print

Connectivity

Wired Network

Gigabit Ethernet (10Base-T/100Base -TX/1000Base -T)

Optional Wireless Network Card¹⁶

2.4GHz: IEEE 802.11 b/g/n (Infrastructure Mode)
IEEE 802.11 g/n (Wi-Fi Direct) (Optional NC-9000W)

Wi-Fi Direct^{†16}

Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported)

Wireless Setup Support¹⁶

Wi-Fi Protected Setup (WPS)

Wireless Applications¹⁶

Vertical Pairing

Mobile

Print or scan from your mobile device with Brother Mobile Connect, AirPrint, Mopria

Local Interface

Hi-Speed USB 2.0, USB 2.0 Host (Rear)

Fleet Management Tools⁵

Unattended Installer⁴

Ability to centrally deploy and customise our drivers and software

MSI Installer⁴

Modular installers that can be distributed through On-Premise Active Directory®

BRAdmin⁴

LAN/WAN management software

Embedded Web Server

Using the IP address or node name of your device, access via a web browser the web based print management software embedded onto the device using an encrypted password

Driver Deployment Wizard⁴

Easily create print drivers for hassle free deployment over your network

Mass Deployment Tool⁴

Provides a configuration interface to help manage and deploy device settings

Status Monitor⁴

Monitor the status of your machine from your computer

Software⁵

Brother iPrint&Scan

Simplified, one-touch shortcuts for easy desktop printing and device maintenance. Easily print or organise your files from your Windows PC or Apple Mac computer

Brother Utilities

Provides setup guides, manual, FAQ & troubleshooting and contact to Brother customer service

Easy Setup²²

Simplifying the install process with easy access to the right drivers and software for the installation of your Brother machine for your PC

Network Security

Wired Network Security

SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP), SNMP v3, 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos, Ipsec

IPv4

ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, FTP Server, TELNET Server, HTTP/HTTPS server, TFTP client and server, SMTP Client, SNMPv1/v2c/v3, ICMP, Web Services (Print), CIFS client, SNTP client, LDAP

IPv6

NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, FTP Server, TELNET Server, HTTP/HTTPS server, TFTP client and server, SMTP Client, SNMPv1/v2c/v3, ICMPv6, Web Services (Print), CIFS Client, SNTP Client, LDAP

IP Filter

Restrict which network users can or cannot access the device over the network (IPv4 only)

Wireless Network Security^{11, 16}

WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (TKIP/AES), SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP), SNMP v3, 802.1x (EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos, IPsec

Wireless Setup Support¹⁶

Wi-Fi Protected Setup (WPS)

Display IP Address

The dynamic IP assigned to your device can be displayed on the home screen

Security Features

E-mail Notifications

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

E-mail Reports

Receive usage reports on a regular basis via e-mail

Automatic Intrusion Detection

All Brother Print devices are secure by design. Devices automatically recognise security attacks and take preventative measures, including rebooting where necessary, in order to ensure the device remains secure.

Digitally-signed Firmware

The firmware for Brother Print devices is digitally signed and secure

On-Premise Active Directory/LDAP Authentication

Utilise existing infrastructure to restrict access to Brother devices using AD/LDAP. Staff can easily use their existing network login credentials to authenticate

Port-based Network Access Control

(IEEE 802.1x)
Brother devices are in full compliance with this standard, to allow connection to an 802.1x EAP (Extensible Authentication Protocol) protected network

Restrict Network Protocols

The Protocol Control feature allows an administrator to restrict communication protocols (e.g. FTP, Telnet) as required

Setting Lock

Secures access to the devices control panel by locking it

Secure Function Lock 3.0

Use a 4 digit pin or a password to identify and authenticate an individual or groups of users over a network. Allows access control with username for up to 200 users

Cloud Secure Print¹⁰

Enables password protected driverless print job release

Store Print Log

Allows the audit of a print log file saved to CIFS server. Record ID, type, name, user, date, time, page count for every print job

Firmware Updates

In addition to allowing automatic updates to the latest version the printer can be set to not receive older firmware versions to avoid downgrade by unauthorised user

SysLog

Allows IT Admin to access a single application (SIEM tool) to get device status updates for audit purposes over Syslog

Developers

Brother Solutions Interface (BSI)

Create powerful cloud and on premise solutions directly integrating the advance print, scan and security capabilities of Brother devices. For more information contact Brother International South Africa.

Near-Field Communications (NFC) / Card Reader Support*

Integrated NFC Reader
Supported NFC standards include: (ISO14443 Type A) MIFARE Standard/Plus/Ultralight/Ultralight C/DESfire my-d move, Tag-it (ISO15693 Type B)

External NFC Card Reader Support
RFIDeas pcProx Enroll

- RDR-6081AKU
- RDR-6281AKU
- RDR-6381AKU
- RDR-6E81AKU
- RDR-6H81AKU

RFIDeas AIR ID Enroll

- RDR-7081AKU
- RDR-7581AKU
- RDR-7F81AKU

Elatec

- TWN3 MIFARE
- TWN3 MIFARE NFC
- TWN3 Multi ISO
- TWN4 MIFARE NFC

(3rd party card readers require additional purchase. Other card readers supported if registered via the embedded web server)

* Not supplied by Brother International

Warranty

3-Year On-Site Warranty

When you purchase a Brother printer and our genuine inks or toners, we'll support you every step of the way with our FREE 3-year warranty commitment. YOU DO NOT NEED TO REGISTER YOUR PRODUCT, our warranty is automatic when you purchase your Brother printer. To keep your Brother machine running in optimal condition we recommend using only Brother Genuine Consumables, this will ensure you automatically enjoy our exclusive 3-year warranty.



*Effective 1 September 2025. Only valid for purchases in South Africa.

Supplies¹, Upgrades and Accessories

- Inbox Toner**
1 x 9,000 pages (BK)
3 x 6,500 pages (C/M/Y)
- Super High Yield Toner**
TN871XXL
1 x 15,000 pages (BK)
3 x 12,000 pages (C/M/Y)
- Drum Unit**
DR851CL
Approx 100,000 pages at 3 pages per job
- Belt**
BU800CL
Approx. 150,000 pages at 2 pages per job
- Waste Toner**
Approx 100,000 pages
WT800CL

- Carton Contents**
Printer, Inbox Toners, Drum, Belt, Waste Toner Box, Power Supply Cord, Quick Set-Up Guide, USB cable
- Wi-Fi Module**
NC-9000W
Optional wireless network interface

- Optional Paper Trays²**
500 sheet tray LT-340CL
4 x 520 sheet tower tray TT-4000
Tower Tray Connector TC-4100
Maximum combinations of 2x LT-340CL, TT-4000 and TC-4100
- Optional Finishing Options²**
Mailbox MX-4000
100 sheets x 4 bins, convertible to 400 sheets x 2 bins

Dimensions and Weights

Printer without Carton (WxDxH)

442 x 541 x 403mm - 29kg

Printer with Carton (WxDxH)

557 x 628.2 x 633.5mm - 34.3kg

Optional Paper Trays (WxDxH)

500 sheet tray:

410 x 486 x 133mm - 6.6Kg

4 x 520 sheet tower tray:

660 x 660 x 717.4mm - 46.6Kg

Tower Tray Connector:

444 x 486 x 103mm - 5.9Kg

Finishing Options (WxDxH)

4 bin Mailbox:

367 x 416 x 381mm - 4.4Kg

Duty Cycle

Recommended Monthly

Up to 12,000 pages monthly print volume

Environment

Power Requirement

220-240V

AC 50/60Hz

Power Consumption¹²

Printing - 770W

(420W in quiet mode)

Ready 85W

Sleep 15.6W

Deep Sleep 1W

Power Off 0.04W

Sound Pressure¹³

Printing 56.5dbA

Ready 17.2dbA

Quiet Mode 53dbA

Sound Power¹⁴

Printing 6.88BA

Ready 3.02BA

Quiet Mode 6.68BA

TEC Value

0.662kWh / Week

Operating Environment

Humidity 20 - 80%

10°C - 32°C

50°F - 90°F

Storage Environment¹⁴

Humidity 10 - 90%

0°C - 40°C

32°F - 104°F

Disk Space Requirements

50MB - Windows Drivers Only
1.6GB - Windows 11, 10, 8.1, 7
All applications inc Drivers
macOS - 500MB All applications

- 1 Approx declared toner yield value in accordance with ISO/IEC 19798
- 2 Calculated with 80gsm sheets of paper
- 3 Windows and macOS
- 4 Windows only
- 5 Free download from the Brother Solutions Centre <http://solutions.brother.com>
- 6 Number of printed pages per month can be used to compare designed durability between Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that exceeds your print requirements
- 7 Requires Brother Software
- 8 Based on ISO/IEC 24734
- 9 Based on ISO/IEC 17629
- 10 Requires an Internet connection
- 11 Wi-Fi Direct supports WPA2-PSK (AES) only
- 12 All values are approximate; power consumption varies depending on the usage environment or part wear
- 13 Based on ISO 7779
- 14 Based on RAL-UZ171
- 15 Requires additional activation
- 16 Optional Wireless Network Card required (NC-9000W)
- 17 Third Party USB hubs not supported
- 18 Win7 / Server2008 SP2/R2 Extended Security Update (ESU) legacy support until 10/01/2023
- 19 Requires installation of optional trays
- 20 Set only a single sheet
- 21 On macOS AirPrint only
- 22 For more information visit <https://setup.brother.com>



Brother International South Africa
96 Sovereign Drive, Route 21 Corporate Park, Irene
Tel 0861 brother Email info@brother.co.za
www.brother.co.za <https://support.brother.com/>



All specifications correct at time of publication and are subject to change without notice. Brother and its logo are trademarks of Brother Industries LTD., Japan.
All registered trademarks referenced herein are the property of their respective companies.