

# Professional 4-in-1 Colour Laser Printer

Robust, high-quality,  
and responsibly designed

Meet the MFC-L8730CDW. Engineered for performance in a compact, eco-friendly design. With fast print and scan speeds, seamless connectivity, and strong security features, it's built to simplify workflows and enhance productivity - without taking up valuable space.

## MFC-L8730CDW

### Key features

- Print or Copy up to 31ppm
- 2-Sided Print or Copy, up to 20 sides per minute
- WiFi 2.4GHz
- Gigabit ethernet
- 250 Sheet paper tray
- 50 Sheet Multi-Purpose input tray
- Auto paper low/empty detection
- 3,000 black, 1,800 colour page yield toners



PRINT



SCAN



COPY



FAX



WIRELESS

**FPOT**  
Less than  
9.9 Seconds

**2-SIDED**  
Scan up to  
56ipm

**NFC**  
Secure  
Authentication

## Playing our part for Sustainability

Smarter Packaging.  
Lighter Environmental Impact.

Brother continues to advance sustainability through engineering innovation. Brother's new printer series features EPS-free, recyclable packaging engineered for reliable protection and logistics efficiency.



### Workflow

#### Built for business efficiency

- Monitor and control your Brother fleet with network-based management tools
- Boost efficiency with high-speed scanning for faster document processing

### Productivity

#### Reliable performance, made to last

- Robust design, built for demanding businesses
- High-yield toners keep you printing without interruptions
- Keep printing for longer with scalable paper capacity
- Streamlined design, up to 25% smaller than previous model



## Secure by design

### Device Security

Your device protects your business by minimising attack surfaces through:

- Secure user access via LDAPS, Active Directory, and NFC authentication
- Controlled privileges using Secure Function Lock and Setting Lock
- System integrity ensured by intrusion detection, Secure Boot, and digitally signed firmware

### Network Security

Your network is protected with flexible, industry-standard tools including:

- Intrusion protection through protocol control, interface restrictions, and IPv4 filtering
- Secure connections via IEEE 802.1X for enterprise wired and wireless networks
- Encrypted communication using TLS, SSH, IPSEC, HTTPS, and SNMPv3
- Centralised management with Device Master Settings, BRAdmin Pro 4, and Mass Deployment Tool
- Syslog reporting for seamless real-time SIEM integration

### Document Security

Your documents are protected through:

- Encrypted transfer via IPPS/HTTPS for printing and TLS, HTTPS, SFTP for scanning
- Non-persistent memory, ensuring data is wiped after each job or reboot
- Secure print release, so documents only print when you're ready to collect them
- 3rd party integration via Brother Solutions Interface (BSI), to streamline workflows



## Supplies

### Toners



**TN665** (inbox)  
3,000 BK, 1,800 CMY

**TN665XXL**  
7,500 BK, 6,500 CMY

**TN667**  
10,000 BK/CMY

## Accessories

### Optional Lower Trays

**LT-350CL**  
250 Sheet Lower Tray x 2 pcs  
(Max 500 sheets)

## Replaceable parts



**Drum Unit**  
DR665CL  
Approx. 50,000 pages  
(3 pages/job)



**Belt Unit**  
BU635CL  
Approx. 100,000 pages  
(3 pages/job)




**Waste Toner Box**  
WT229CL  
Approx. 50,000 pages  
(5 pages/job)



**Fuser Unit**  
FD-5000  
Approx. 100,000 pages  
(5 pages/job)

**Paper Feed Kit  
for MP Tray**  
PF-M5000  
Approx. 50,000 pages  
(5 pages/job)



## General

### Technology

Electrophotographic (Laser)

### Laser Classification

Class 1 Laser Product

### Memory

512MB internal

### Processor

1200 MHz

### Control Panel

8.8cm Colour  
Touchscreen LCD

### Local Interface<sup>18</sup>

Hi-Speed USB 2.0,  
USB 2.0 Host (Front)

### Wired Network interface

GigE (10Base-T/100Base-  
TX/1000Base-T)

### Fax Interface

Telephone Line port  
External Telephone Answering  
Device port (TAD)

### Configurable Shortcuts

Add, delete, change up to 48  
personalised shortcuts for quick  
and secure access to device  
functions

### Wireless Network interface

2.4GHz: IEEE 802.11b/g/n  
(Infrastructure Mode),  
Vertical Pairing

### Wi-Fi Direct<sup>®</sup>

Print wirelessly without having  
to use a wireless access point  
(both automatic and manual  
methods supported)

## Warranty

### Brother 3-Year Warranty

When you purchase a Brother printer and our genuine inks or toners, we'll support you every step of the way with our FREE 3-year\* warranty commitment. YOU DO NOT NEED TO REGISTER YOUR PRODUCT, our warranty is automatic when you purchase your Brother printer. To keep your Brother machine running in optimal condition, we recommend using only Brother Genuine Consumables, this will ensure you automatically enjoy our exclusive 3-year\* warranty.

\*Effective 1 September 2025. Valid only for products purchased in South Africa.



## Print<sup>9,24</sup>

### Print Speed (A4)

Up to 31ppm  
(pages per minute)

### Print Speed 2-Sided (A4)

Up to 20 sides per minute  
(10 sheets per minute)

### Resolution

2,400dpi (2,400 x 600dpi),  
600 x 600dpi  
(Horizontal x Vertical,  
dots per inch)

### FPOT

#### (First Print out Time)

Less than 9.9 seconds from  
ready mode and standard tray

### Warm up Time

Less than 15.1 seconds from  
sleep mode

## Driverless Printing Compatibility

### Windows Modern Print Platform Ready

Supports seamless, driverless  
printing via IPP for instant setup  
on Windows 10 (21H2+) and  
Windows 11 devices

### Mopria

Print common file types  
from supported Android  
mobile devices and Windows  
computers

### Apple AirPrint

Print common file types from any  
AirPrint enabled application

### ChromeOS™

Supports Work with  
Chromebook printing

Our printers support driverless printing across Windows, macOS, iOS, and Android devices for instant, secure, and hassle-free setup

## Printer Functions

### Direct Print

Print directly from the front USB host port using a USB flash memory drive. Supported formats include; PDF 2.0, JPEG, TIFF (scanned using Brother model)

### Print Complete Notice

A notification can be set to go to your computer when printing

### Manual 2-Sided Print<sup>4,25</sup>

Manual 2-sided printing recommended for media not supported by automatic 2-sided print

### Carbon Copy<sup>4</sup>

Prints additional copies of the same document to paper taken from additional paper trays

### Header Footer Print<sup>3,25</sup>

Add the date, time, login user name, or custom text to the top or bottom of each printed page

### N-up Printing<sup>3</sup>

Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page, Mac (Airprint) up to 2, 4, 6, 9, or 16

### Poster Printing<sup>4,25</sup>

Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages

### Watermark Printing<sup>3,25</sup>

Watermark your documents with predefined or user-defined text

### Secure Print<sup>3</sup>

Protect print jobs with a release code required at the device in order for them to be printed

## Paper Handling

### Paper Input<sup>2</sup>

#### Standard (Tray 1)

250 Sheets

#### Multi Purpose Tray

50 Sheets, 10 Envelopes

#### Automatic Document Feeder (ADF)

80 Sheets

### Paper Output<sup>2</sup>

150 sheets face down

1 sheet face up (straight path)

### Media Sizes

#### Standard (Tray 1)

Letter, Legal, Executive, A4, A5, A5 (Long Edge), A6, Mexico Legal, India Legal, Folio, 16K (195 x 270mm)

#### Multi Purpose Tray

Width: 76.2mm - 216mm

Length: 116mm - 355.6mm

Envelopes; C5, Com-10,

DL, Monarch

#### Optional Trays

Letter, Legal, Executive, A4, A5, Mexico Legal, India Legal, Folio, 16K (195 x 270mm)

#### Automatic Document Feeder (ADF)

Width: 105 - 215.9mm

Length: 148 - 355.6mm

### 2-sided Print

A4

### Media Weights

#### Standard (Tray 1)

60 - 105gsm

#### Multi Purpose Tray

60 - 163gsm

#### Optional Trays

60 - 105gsm

#### Automatic Document Feeder (ADF)

60 - 105gsm

### Media Types

#### Standard (Tray 1)

Thin Paper, Plain Paper, Thick Paper, Recycled Paper

#### Multi Purpose Tray

Thin Paper, Plain Paper, Thick Paper, Recycled Paper, Bond Paper, Label, Envelope, Env. Thin, Env. Thick, Glossy Paper<sup>20</sup>

#### Optional Trays

Thin Paper, Plain Paper, Recycled Paper

#### Auto 2-Sided Print

Thin Paper, Plain Paper, Thick Paper, Thicker Paper, Recycled Paper, Glossy paper

#### Automatic Document Feeder (ADF)

Thin Paper, Plain Paper, Recycled Paper

### Paper Input Sensors

Onscreen and optional email alert notifications when input trays are empty or running low

## Copy<sup>10</sup>

### Copy Speed (A4)

Up to 31 cpm  
(copies per minute)

### Copy Speed 2-Sided (A4)

Up to 20 sides per minute  
(10 sheets per minute)

### FCOT

#### (First Copy Time Out)

12.5 seconds from ready mode  
and standard tray

### Resolution

Print up to 1,200 x 600dpi  
(Horizontal x Vertical, dots  
per inch)

## Copy Functions

### Multi-Copying

Ensures that your copies are  
organised in the correct order,  
making it easier to manage large  
documents. Makes up to 999  
copies of each page

### Enlargement/Reduction Ratio

Reduce or Increase document  
sizes from 25% to 400% in  
1% increments

### N in 1 Copying

Allows the user to compress 2 or  
4 pages on to a single A4 sheet

### Automatic 2-Sided Copying

Scans and copies documents  
using the Automatic Document  
Feeder (ADF)

## Scan

### Scan Speed Standard (A4)

Colour and Mono (2 Sided)<sup>11</sup>  
Up to 56ipm  
(images per minute)

### Optical Scan Resolution

ADF Up to 600 x 600dpi  
Flatbed Up to 1,200 x 1,200dpi  
(Horizontal x Vertical,  
dots per inch)

### Interpolated Scan Resolution<sup>22</sup>

Up to 19,200 x 19,200dpi  
(Horizontal x Vertical, dots per  
inch)

### Scanner Type

Dual CIS (Contact Image Sensor)

### Colour Depth

48 bit colour Processing (Input)  
24 bit colour Processing (Output)

### Grey Scale

256 levels (8 bit)

## Scanner Functions

### Windows<sup>5</sup>

TWAIN & WIA

### Macintosh<sup>23</sup>

AirPrint Scanning  
macOS 10.14.x or greater

### Linux<sup>5</sup>

SANE (32 & 64 bit editions)

### Machine File Formats

Including PDF (PDF/A, Secure PDF, Signed PDF, High Compression PDF, Multi-page PDF), JPEG, TIFF

### Standard Machine Functions<sup>7</sup>

Scan to USB, E-mail, OCR, Image and File

### Network Scanning

Scan to network folder (SMB)<sup>4</sup>, SFTP, FTPS, Email Server, HTTPS, SharePoint (on premise)

### Machine Scanning Features

Auto Deskew from ADF, Background Colour Drop, Auto Crop, Blank Page Removal

### Scan Profile

Create up to 25 preset network profiles for an easy way to store multiple scan settings

### Direct Scan

Scan directly to a USB flash memory storage

### ChromeOS™

Supports integrated Chrome OS scanning functionality

### Scan Preview

The contents of Scan to FTP, Network, Email Server, HTTP, Sharepoint (on premise) can be checked before sending to destination

### Scan Margin

Setting the scan margin to 0mm removes the default 3mm margin, allowing the scanned image to capture the entire document without any border

## Fax

### Fax Modem

33,600bps (Super G3)

### Transmission Speed

Approx. 2.5 sec (ITU-T Test Chart Document No.1, Std resolution, JBIG) Quick-Scan Approx. 1.82 sec/page

### Fax Send Resolution

Std resolution 203 x 98dpi up to 203 x 392dpi (Horizontal x Vertical, dots per inch)

### Automatic 2-Sided Faxing

Scans and faxes documents using the Automatic Document Feeder (ADF)

### Grey Scale

256 shades (8 bit) of grey are available for faxing

### Memory Transmission | Out of Paper Reception

Up to 500 pages (ITU-T Test Chart, Standard Resolution, JBIG)

### Compression Methods

Ranging from basic to advanced with MH, MR, MMR, JBIG

## Fax Functions

### PC-Fax Send<sup>7</sup> and Receive<sup>4,7</sup>

Send and Receive black & white faxes directly from your PC

### Internet Fax (I-Fax)

Fax documents over the internet as an email TIFF attachment

### Fax to Server

Scan a document and send it over the network to a separate fax server

### Automatic Redial

Automatic redialling if the recipient fax is busy

### Telephone Index

An electronic, alphabetical listing of stored speed dials and group numbers

### Chain Dialing

Allows the user to store parts for long dialing sequences in different speed dial locations

### Dial Restriction

Restrict number dialing to prevent unauthorised or accidental outbound calls

### Error Correction Mode

ECM detects line errors during fax transmission and resend the page(s) of the document that had an error (recipient machines must share this feature for it to work)

### Batch Transmission

Stores documents for the same location in the machines memory for transmission in a single call

### Auto Reduction

When receiving a single page document longer than A4 (297mm) the fax machine will automatically reduce the message to fit onto a single A4 sheet

### Fax Stamp

Add the date and time to all received faxes

### Cover Page

Create custom cover pages for outgoing faxes

### Broadcasting

Send the same fax message up to 350 locations (manual 50 locations)

### Fax Forwarding

Sends a fax received in memory to another pre-programmed fax number

### Remote Retrieval

Allows users to remotely access their machine and retrieve stored fax messages

### Station ID

An ID and fax number will be printed as the header of every fax sent

### PBX

Enables seamless fax operation in office environments by supporting PBX phone systems

## Connectivity

### Mobile Connect

Use a Brother app to Print from and scan to a mobile device running iOS or Android operating system

### Brother Print Service Plugin<sup>5</sup>

Print from Android devices without a dedicated App

### Microsoft Universal Print

Organisations can manage their brother print infrastructure through cloud services from Microsoft

### Brother Apps<sup>12</sup>

Cloud Secure Print, Scan to; mobile, Searchable PDF, Microsoft PowerPoint, Word, Excel, Easy Scan to email, and Fax Forward to Cloud/Email

### Web Connect<sup>12,16</sup>

Without a PC you can download to print and upload from scan and fax for Box, Microsoft SharePoint Online, Dropbox, Evernote, OneDrive, Google Drive™, OneNote

### Email Print<sup>12,16</sup>

Enables driverless printing via email

## Fleet Management Tools<sup>5</sup>

### BRAdmin<sup>4</sup>

LAN/WAN management software

### Auto Pull Configuration

The device periodically checks an encrypted settings file on a network location. If the device has been changed the file is used to change back to the desired state configuration

### Embedded Web Server

Using the IP address or node name of your device access via USB or network via a web browser to the web based print management software embedded onto the device using a randomly encrypted password

### Mass Deployment Tool

Provides a configuration interface to help manage and deploy device settings.

## Software<sup>5</sup>

### Brother iPrint&Scan

Print from, scan to, preview copies and check the machine status from Windows or macOS PC using Brother software

### Print Support App<sup>4</sup>

As an alternative to Windows Modern Print this method enhances compatibility and ease of use by enabling printing without traditional printer drivers, making it a versatile and efficient solution for modern printing needs accessible through the Microsoft Store

Visit: [support.brother.com](http://support.brother.com) for the full list of supported OS and to download the latest software  
All trademarks, brand and product names are property of their respective companies

## Legacy Printer Drivers<sup>24</sup>

### PCL Driver<sup>4</sup>

Generic PCL XL driver

### Universal Printer Driver<sup>4</sup>

BR-Script3 Driver that enables printing to any network or locally connected Brother laser printer that supports PostScript

### Print Languages

PCL6, BR-Script3, PDF Version 2.0

### Embedded Fonts (PCL)

73 scalable fonts, 12 bitmap fonts

### Embedded Fonts (BR-script)

66 scalable fonts

### Embedded Barcodes (PCL)

16 bar codes fonts - Code39, Interleaved 2 of 5, FIM (US-PostNet), Post Net (US-PostNet), EAN-8, EAN-13, UPC-A, UPC-E, Codabar, ISBN (EAN), ISBN (UPC-E), Code128 (set A,B, C), EAN128 (set A,B,C), Code93, GS1Databar, MSI

### Linux

Printer Driver (Linux, CUPS, LPD/LPRng)

## Network Security

### Wired Network Security

APOP, SMTP-AUTH, SSL/TLS (IPP, HTTP, SMTP, POP3, IMAP4, FTP, LDAP), SNMP v3, 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), OAuth(SMTP, POP3, IMAP4), Kerberos, IPsec

### Wireless Network Security

WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (TKIP/AES), WPA3-SAE (AES), APOP, SMTP-AUTH, SSL/TLS (IPP, HTTP, SMTP, POP3, IMAP4, FTP, LDAP), SNMP v3, 802.1x (EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), OAuth (SMTP, POP3, IMAP4), Kerberos, IPsec Wi-Fi Protected Setup® (WPS)<sup>13</sup>

### IPv4

ARP, RARP, BOOTP, DHCP, APIPA (Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLNMR responder, LPR/LPD, Custom Raw Port/Port9100, POP3, SMTP Client, IPP/IPPS, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, Web Services (Print/Scan), SNTP Client, LDAP, LDAPS, IMAP4, Syslog

### Display IP Address

The dynamic IP assigned to your device can be displayed on the home screen

### IPv6

NDP, RA, DNS resolver, mDNS, LLNMR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, POP3, SMTP Client, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMPv6, Web Services (Print/Scan), SNTP Client, LDAP, LDAPS, IMAP4, Syslog

### IP Filter

Restrict which network users can or cannot access the device over the network

## Security Features

### E-mail Notifications

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

### E-mail Reports

Receive usage reports on a regular basis via e-mail

### Secure Boot

All Brother Print devices are secure by design. Devices automatically recognise security attacks and take preventative measures, including rebooting where necessary, in order to ensure the device remains secure

### Digitally-signed Firmware

The firmware for Brother Print & Scan devices is digitally signed and secure

### Active Directory/LDAP Authentication

Utilise existing infrastructure to restrict access to Brother devices using AD/LDAP. Staff can easily use their existing network login credentials to authenticate

### Port-based Network Access Control

(IEEE 802.1x)  
Brother devices are in full compliance with this standard, to allow connection to an 802.1x EAP (Extensible Authentication Protocol) protected network

### Restrict network protocols

The network access control feature allows an administrator to restrict communication protocols (e.g. FTP, Telnet) as required

### Setting Lock

Secures access to the devices control panel by locking it

### Secure Function Lock 3.0

Use a 4 digit pin or a password to identify and authenticate an individual or groups of users over a network. Allows access control with username for up to 200 users

### Store Print Log

Allows audit of a print log file saved to CIFS server. Record ID, type, name, user, date, time, page count for every print job

### Firmware Updates

In addition to allowing automatic updates to the latest version the printer can be set to not receive older firmware versions to avoid downgrade by an unauthorised user

### SysLog

Allows IT Admin to access a single application (SIEM tool) to get device status updates for audit purposes over Syslog

## Near-Field Communications

### NFC Card Reader

Supports secure user authentication via NFC card reader for access control, and enables personalised workflows through NFC Shortcut configuration. Third-party card reader support requires additional purchase and can be connected to the front USB host and registered via the embedded web server

## Address Book

### Speed Dials

300 locations for E-mail addresses and fax numbers

### Group Dial

A combination of up to 20 groups can be stored

### LDAP

The ability to connect to an external LDAP enabled address book, like Microsoft Exchange

## Developers

### Brother Solutions Interface (BSI)

Create powerful cloud and on premise solutions directly integrating the advanced print, scan and security capabilities of Brother devices.

## Supplies<sup>1</sup>, Upgrades and Accessories

### Inbox Toner

3,000 pages (BK)  
1,800 pages (CMY)

### Standard Toner

TN665  
3,000 pages (BK)  
1,800 pages (CMY)

### Super High Yield Toner

TN665XXL  
7,500 pages (BK)  
6,500 pages (CMY)

### Ultra High Yield Toner

TN667  
10,000 pages (BK)  
10,000 pages (CMY)

### Drum Unit

DR665CL approx 50,000 pages at 3 pages per job

### Belt Unit

BU635CL approx. 100,000 pages at 3 pages per job

### Waste Toner Box

WT229CL approx 50,000 pages at 5 pages per job

### Fuser Unit

FD-5000 approx 100,000 pages at 5 pages per job

### Paper Feed Kit for MP Tray

PF-M5000 approx 50,000 pages at 5 pages per job

### Carton Contents

Machine, Inbox Toners, Drum, Belt, Waste Toner Box, Fuser, PF Kit, Power Supply Cord, Quick Set-Up Guide, Warranty Card, USB Cable included

### Optional Paper Trays<sup>2</sup>

250 sheet tray (LT-350CL)  
Maximum combinations of up to 2 x LT-350CL

## Dimensions and weights (WxDxH)

**Printer w/o Carton**  
404 x 473 x 460mm - 25.6kg

**Optional Paper Trays**  
250 sheet tray:  
404 x 446 x 100mm - 3.25kg

## Duty Cycle

**Recommended Monthly**  
Up to 5,000 pages monthly print volume

**Maximum Monthly<sup>6</sup>**  
Up to 60,000 pages monthly print volume  
Up to 5,000 pages monthly scan volume

## Environment

**Power Requirement**  
AC 220-240V, 50/60Hz

**Power Consumption<sup>14</sup>**  
Printing - 540W  
(330W in quiet mode)  
Copying - 540W  
(330W in quiet mode)  
Ready 60W  
Sleep 8.4W  
Networked Standby 7.8W  
Deep Sleep 0.53W  
Power Off 0.04W

**Sound Pressure<sup>15</sup>**  
Printing: 49dbA  
Quiet Print Mode: 44dbA  
Default Ready: 31dbA

**Sound Power<sup>15</sup>**  
Printing: 6.47BA  
Quiet Print Mode: 5.88BA  
Default Ready: 4.43BA  
Deep Sleep: 3.38BA

**TEC Value**  
0.43 kWh/Week

**Eco Mode**  
With seamless functionality the eco control system of the printer is designed to ensure lower noise levels, consume less energy when not in use and optimise toner usage which all help to reduce the total cost of ownership

**Operating Environment**  
Humidity 20 - 80%  
Temp 10° - 32.5° centigrade  
50° - 90.5° fahrenheit

**Storage Environment**  
Humidity 35 - 85%  
Temp 0° - 40° centigrade  
32° - 104° fahrenheit

## Computer Platforms

**Windows**  
Windows 11  
(Home|Pro|Education|Enterprise)  
Windows 10  
(Home|Pro|Education|Enterprise)  
(32 or 64 bit editions)  
Windows Server  
2025, 2022, 2019, 2016

**Linux**  
Supported Package management System:<sup>23</sup>  
dpkg, rpm

**Macintosh<sup>21</sup>**  
macOS 13 or greater

**ChromeOS™**  
Compatible with Chromebooks, including "Works with Chromebook" certified printing support and integrated Chrome OS scanning functionality

Visit: [support.brother.com](https://support.brother.com) for the full list of supported OS and to download the latest software

## Disk Space Requirements

80MB Windows drivers only, 2GB Windows 11, 10, applications inc drivers

500MB - macOS applications

20MB - Linux drivers only

## Certification

### Wi-Fi CERTIFIED:

Wi-Fi Direct, Wi-Fi Protected Setup, WPA3™ - Enterprise, Personal

### Mopria Certified

Ensures universal compatibility for driverless printing across Windows, Android, and compatible mobile operating systems

### AirPrint

Print common file types from any AirPrint enabled application

1. Approx declared toner yield value in accordance with ISO/IEC 19798. 2. Calculated with 80gsm sheets of paper. 3. Windows & macOS. 4. Windows only. 5. Free download from the Brother Solutions Centre <http://solutions.brother.com> 6. Number of printed pages per month can be used to compare designed durability between Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that exceeds your print requirements. 7. Requires Brother Software. 8. Based on ISO/IEC 24734. 9. Based on ISO/IEC 17629. 10. Based on ISO/IEC 24735. 11. Based on ISO/IEC 17991. 12. Requires an Internet connection. 13. Wi-Fi Direct supports WPA2-PSK (AES) only. 14. Measured according to IEC 62301 Edition 2.0. All values are approximate; power consumption varies depending on the usage environment or part wear. 15. Based on ISO 7779. 16. Requires additional activation. 17. May not be available in your region. 18. Third Party USB hubs not supported. 19. Requires installation of optional trays. 20. Set only a single sheet. 21. On macOS AirPrint only. 22. For WIA, 1200 x 1200 resolution. Brother Scanner Utility enables to enhance up to 19200 x 19200 dpi. 23. Red Hat Enterprise Linux 8.6 64bit, Red Hat Enterprise Linux 9.1 64bit, Fedora 39 64bit, Mageia 9 32bit, Mageia 9 64bit, openSUSE 15.5 64bit, SUSE Enterprise15-SP4 64bit, Debian 12.2.0 32bit, Debian 12.2.0 64bit, Ubuntu MATE 18.04 32bit, Ubuntu 22.04 64bit, Ubuntu 23.10 64bit, Linux Mint 21.2 64bit, Ubuntu 24.04 64bit. 24. Microsoft is transitioning towards driverless printing as the preferred standard. Legacy driver installations remain supported for customers with existing deployment requirements. 25. Advanced settings via legacy driver or the Print Support App only. 26. Compared to Brother's previous equivalent model. 27. Figure based on Brother's internal analysis at the time of publication. Figures may fluctuate depending on manufacturing methods and the availability of materials. 28. These results are based on Brother's internal calculations, compared to previous equivalent model. The CO<sub>2</sub> emissions scope covers C1 (Purchased goods and services), C11 (Use of sold products), and C12 (End-of-life treatment of sold products). Exact values may vary depending on country or region, manufacturing methods and the availability of materials.



**brother**  
at your side

### Brother International South Africa

96 Sovereign Drive, Route 21 Corporate Park, Irene  
Tel 0861 brother Email [info@brother.co.za](mailto:info@brother.co.za)  
[www.brother.co.za](http://www.brother.co.za) <https://support.brother.com/>



**BROTHER**  
**CREATIVECENTRE**



All specifications correct at time of publication and are subject to change without notice. Brother and its logo are trademarks of Brother Industries LTD., Japan. All registered trademarks referenced herein are the property of their respective companies.